

SCR对应电压功率对照表

定阻抗负载

额定 电流	1 ϕ 主电源电压					3 ϕ 主电源电压					SCR 额定电流
	220V	380V	415V	440V	480V	220V	380V	415V	440V	480V	
26A	/	/	/	/	/	9.0	15.5	17.0	18.0	19.6	90%
30A	6.0	10.3	11.3	12.0	13.0	10.4	18.0	19.6	20.7	22.6	90%
42A	/	/	/	/	/	14.5	25.1	27.4	29.1	31.7	90%
45A	9.0	15.5	17.0	18.0	19.6	15.6	27.0	29.4	31.1	34.0	90%
60A	12.0	20.7	22.6	24.0	26.1	20.7	36.0	39.2	41.5	45.3	90%
80A	16.0	27.6	22.6	24.0	26.1	27.7	47.8	52.2	55.4	60.4	90%
100A	20.0	34.5	37.7	40.0	43.6	34.6	59.8	65.3	69.2	75.5	90%
125A	25.0	43.1	47.1	50.0	54.5	43.3	74.8	81.6	86.6	94.4	90%
150A	30.0	51.8	56.6	60.0	65.4	51.9	89.7	98.0	104.0	113.3	90%
180A	36.0	62.1	68.0	72.0	78.5	62.3	107.7	117.6	124.7	136.0	90%
230A	46.0	79.4	86.7	92.0	100.3	79.6	137.6	150.3	159.3	173.8	90%
300A	60.0	103.6	113.1	120.0	131.0	104.0	179.5	196.0	207.8	226.7	90%
380A	76.0	131.2	143.3	152.0	165.8	131.6	227.3	248.3	263.2	287.2	90%
450A	90.0	155.4	169.7	180.0	196.3	155.8	269.2	294.0	311.7	340.1	90%
580A	116.0	200.3	218.8	232.0	253.1	200.9	347.0	379.0	401.8	438.3	90%
720A	144.0	248.7	271.6	288.0	314.1	249.4	430.8	470.0	498.8	544.1	90%

苏州市菲顿电器有限公司

单位：KW

IP灯管、电感性负载

额定 电流	1 ϕ 主电源电压					3 ϕ 主电源电压					SCR 额定电流
	220V	380V	415V	440V	480V	220V	380V	415V	440V	480V	
26A	/	/	/	/	/	9.0	15.5	17.0	18.0	19.6	90%
30A	6.0	10.3	11.3	12.0	13.0	10.4	18.0	19.6	20.7	22.6	90%
42A	/	/	/	/	/	14.5	25.1	27.4	29.1	31.7	90%
45A	9.0	15.5	17.0	18.0	19.6	15.6	27.0	29.4	29.1	31.7	90%
60A	12.0	20.7	22.6	24.0	26.1	20.7	36.0	39.2	41.5	45.3	90%
80A	16.0	27.6	30.1	32.0	35.0	27.7	47.8	52.2	55.4	60.4	90%
100A	(85%) 19	34.5	37.7	40.0	43.6	34.6	59.8	65.3	69.2	75.5	90%
125A	(80%) 23.0	41.3	45.1	47.8	52.1	41.4	71.5	78.1	82.8	90.3	85%
150A	(80%) 27.5	47.5	51.8	55.0	60.0	47.6	82.2	89.8	95.2	104.0	85%
180A	(75%) 31.6	57.0	62.2	66.0	72.0	57.1	98.7	107.8	114.3	124.7	80%
230A	(75%) 40.4	72.8	79.5	84.3	92.0	73.0	126.1	137.7	146.0	159.3	80%
300A	(75%) 52.8	95.0	103.7	110.0	120.0	95.2	164.5	179.7	190.5	207.8	80%
380A	(75%) 66.8	120.3	131.4	139.3	152.0	120.6	208.4	227.6	241.3	263.2	80%
450A	(75%) 79.2	142.5	155.6	165.0	180.0	142.8	246.8	269.5	285.7	311.7	80%
580A	(75%) 102.0	183.6	200.5	212.6	232.0	184.1	318.1	347.4	368.3	401.8	80%
720A	(75%) 126.7	228.0	249.0	264.0	288.0	228.6	394.9	431.2	457.2	498.8	80%

苏州市菲顿电器有限公司

单位：KW